

8	SOUd-SOUd	Sound control frequency flash
9	SUND-SUND	Sound control color change
10	R000-R255	Red color selection, (000- -255) B and C key to modify the color selection
11	G000-G255	Green color selection, (000- -255) B and C key to modify the color selection
12	B000-B255	Blue selection, (000-255) B and C key to modify the color selection
13	W000-B255	White selection, (000-255) B and C key to modify the color selection

c). DMX512 Channel description

d). functional

order number	function	explain
Channel 1	Total dimming	R, G, B, W total dimming, linear dimming, from dark to bright
Channel 2	R aiming	R dimming, linear dimming, from dark to bright
Channel 3	G aiming	G dimming, linear dimming, from dark to bright
Channel 4	B aiming	B dimming, linear dimming, from dark to bright
Channel 5	W aiming	W dimming, linear dimming, from dark to bright
Channel 6	Total frequency flash	R, G, B, W total strobe, from slow to fast
Channel 7	FS	Jump, gradient, voice control
Channel 8	Functional speed	Functional speed, from slow to fast

characteristics:

The operation is very simple, humanized design, dimming without flicker, jitter phenomenon, etc. Can adapt to photography, photography, television stations and other strict requirements on the lighting occasions.

18 instructions for 12-watt RGBWLED stained pallamps



Thank you for choosing the products produced by our company, in order to ensure your safe, reliable and long-term use, to provide you with long-term satisfaction service, I suggest you to make

Read the instructions carefully before using the machine. Safety introduction

- ☐ Confirm that the operating voltage is not higher or lower than the value specified in the instruction manual.
- ☐ Confirm that the power cord was not cut or damaged by the blade.
- ☐ The ps must be disconnected when not in use or before cleaning.
- ☐ Only allowed to use the plug, please do not pull the power cord to unplug the plug.

pay attention to:

- ☐ Be careful when installing the lamps to avoid touching exposed wires that can cause fatal clicks.
- ☐ Do not look directly at the light source when using the light lamp, otherwise the eyes will be damaged.
- ☐ Please note that the lamps should be kept away from young children and non-professionals.

Operation regulations

- ☐ This lamp is only allowed under the power supply conforming to the lamp, and is only suitable for indoor use.
- ☐ Do not shake the lamps at will when using, and please do not operate rough when installing or using the lamps.
- ☐ In the selected installation location is, make sure that the lamp is not exposed to extremely hot, wet or dusty places; the distance between the lamp and the exposed object must exceed 0.5 m.
- ☐ Connect the lamps with suitable, secure wiring.
- ☐ Please operate them after being familiar with the functions of the lamps. Most of the damage of the lamps is caused by improper operation, so non-professionals are not allowed to operate the lamps.
- ☐ Please do not modify the lamps at will. Due to the disassembly of the lamps, repair and modification by the manufacturer or non-professional personnel. The manufacturer does not provide any warranty.

technical feature

◆ Adopt 543W LED semiconductor luminescence technology, stepless dimming control system, high brightness, low power consumption, silent operation, long service life of light source (100,000 hours); total power: 180W


◆ Using multimedia grayscale adjustment technology, using the DMX

console to control a variety of color changes;

- ◆ With the electronic address code setting;
- ◆ The specially designed hanging device enables the digital PAR lights to be installed in any direction on the lamp frame;
- ◆ Light-emitting devices: ultra-high brightness LED;
- ◆ Base color: red, green, blue and white;
- ◆ DMX channel: 8 CH control mode: voice control, master-slave, 512 control, built-in program
- ◆ Dimdimming: linear dimming
- ◆ Strobe: 1-8f / s

Function Settings:

A) Graphical part:



- A.function key
B.additional key
C. The key reduction
A B C D D.
Determine the key

Operation instructions: pressing function key A will cycle 13 different functions, and the first two digits of the digital tube represent the current function (refer to the function table). The last two numbers represent the function of this kind.address code. Or the speed, the parameters of the. Press either B or C to modify the parameter values. Press the key D to confirm.

B) LED display window function control table (all functions are selected and then press A to confirm)

order number	show	function declaration
1	A 001-A512	8-channel address code, (001- -512) Key B and C keys add or subtract the address code value
2	ADYE-YDNO	512 Priority to open and close
3	AU 0I-AU08	(01—08) B, C Colorful color selection
4	FF00-FF99	(01- -99) Colorful colors B, C self-walking, color change, speed

5	EE00-EE99	(01—99) B, C color gradient, from slow to fast
6	CC00-CC99	(01—99) B, C color pulse change, from slow to fast
7	F000-F255	Strobe, from slow to fast

Input voltage: AC100-240V, 50-60 HZ

Rated power: 200W

LED light source: 1812W red, green, blue and white bright four colors

Colour temperature: 2000K-10000K

Life of lamp beads:> 20000h

Number of channels: standard 8 CH

Standard DMX512,3-core interface, self-go,

Master and slave control mode: High-speed strobe: 1-25 HZ

Linear dimming: 0-100% linear dimming

Waterproof grade: IP 20

Product net weight: 4.35kg

Appearance dimensions: 22x22x13.5cm

Single carton size; 25 x25x 36cm

One six; 78 x 52x 38cm one six total weight; 20 KG

One pack of ten flight box size; 126.5x 52x 41cm

Net weight of air compartment; 23.6KG gross weight of air compartment; 67.2KG