

Wifi RGBWW User Guide

- 1) **Hard wire the transformer lead:** Without connecting to the GFI Outlet, hot wire the 120V plug to the 120VAC Input on the transformer (Red Taped Line). Hot wire black with black and white with white. Add an endcap to the green wire. Make sure the transformer is installed where it has access to wifi.
- 2) **Download App:** Download Smart Life or Tuya App from your App Store/Google Play and create an account. You can also scan the QR code on the transformer to download.
- 3) **ID Each Light:**
 - a) Carefully unpack your RGBWW LED
 - b) Insert the first Smart LED into your light fixture, then hardwire to the transformer directly. **Note:** Do this 1 fixture at a time.
 - c) Open up the app, and click the + Icon at the top right-hand corner > Add Device.
 - d) **Note:** To automatically add devices, the app must be connected to wifi & bluetooth permissions. Only **2.4 GHz** Wi-Fi networks are supported.
 - e) The bulb will start blinking/breathing once it's picked up by the radar.
 - f) Add Wifi info as required by the app and confirm
 - g) Edit the name of the fixture to reference each light: "Tree 1 Front Yard".
 - h) Note: This light should work with bluetooth and wifi off. Disconnect both from you phone and make sure the bulb is still responsive. If it is, then proceed to next step, if not, then repeat the process with both BT and Wifi off.
 - i) Disconnect the light, and add the next light fixture. Make sure to tag each light with the same name as placed on the app to not getting them mixed up. Repeat the process for each light until each one has an ID.
 - j) Once each Light has its respective ID, you can lay them at the desired location for installation. As long as the transformer is connected to wifi, you'll be able to control all the lights from any distance
- 4) **Create Groups:** You have the option to create groups, for example: All Driveway lights, or all front yard. To do this, go to the home page on the app, select any light, and on the top right-hand corner, select the 3 dots, then choose the option create group, and add as many as you want to the group. Add the name to the respective group to finish the step. You can add "The Group" to the home page for easy access. Just click on the "All Devices" option on the home page, hard press on the "The Group", and click "Add to home".
- 5) **Other Features:** You can create Scenes, change color, dim, connect to home devices, set schedule and so on

Troubleshooting:

If the first bulb is not connecting, make sure you are correctly connected to a 2.4 Ghz wifi. While the light fixture is connected to the transformer, and the transformer on, connect and disconnect the bulb repeatedly 7-8 times. The bulb should start blinking and/or breathing, this means the bulbs are reset and in pairing mode. If this does not work, keep the bulb inserted in the light fixture, and plug & unplug the transformer 5 times repeatedly to reset the whole system, the bulbs will start breathing/blinking.

Espanol:

Guía de Usuario - RGBWW WiFi

Cableado del transformador:

Sin conectar a la toma GFI, conecta el cable de 120V al terminal de entrada 120VAC del transformador (línea con cinta roja). Conecta negro con negro y blanco con blanco. Coloca un capuchón en el cable verde. Asegúrate de que el transformador esté instalado en un lugar con acceso a WiFi.

Descargar la App:

Descarga la app **Smart Life** o **Tuya** desde el App Store o Google Play y crea una cuenta. También puedes escanear el código QR que está en el transformador para descargarla.

Cambiar a Modo App:

Una vez que el transformador esté encendido, cambia de “Control Mode” a “App Mode” presionando el botón “Enter”. El indicador del botón parpadeará durante unos segundos. Luego puedes seguir los siguientes pasos para conectar el transformador a tu teléfono.

Identificar Cada Luz:

- Desempaqueta con cuidado tu LED RGBWW.
- Inserta el primer foco inteligente en tu luminaria y conéctalo directamente al transformador.
Nota: Haz esto **una luminaria a la vez**.
- Abre la app y presiona el ícono + en la esquina superior derecha > Agregar dispositivo.
Nota: Para que los dispositivos se agreguen automáticamente, la app debe tener acceso a WiFi y Bluetooth. Solo se admiten redes WiFi de **2.4 GHz**.
- La bombilla comenzará a parpadear o a hacer un efecto de “respiración” cuando sea detectada.
- Ingresa la información de WiFi solicitada por la app y confirma.
- Cambia el nombre del dispositivo para identificarlo, por ejemplo: “Árbol 1 Jardín Frontal”.
- Desconecta la luminaria e instala la siguiente. Asegúrate de etiquetar cada luz con el mismo nombre que le diste en la app para no confundirlas.

- Repite el proceso con cada luminaria hasta que todas tengan su propia identificación.
 - Una vez identificadas, puedes colocarlas en su ubicación final. Siempre que el transformador esté conectado al WiFi, podrás controlar todas las luces desde cualquier distancia.
-

Crear Grupos:

Tienes la opción de crear grupos, por ejemplo: Todas las luces del camino de entrada o todo el jardín frontal.

Para hacerlo:

- Ve a la página principal de la app.
 - Selecciona cualquier luz.
 - En la esquina superior derecha, presiona los 3 puntos > “Crear Grupo”.
 - Agrega todas las luces que desees al grupo.
 - Asigna un nombre al grupo para finalizar.
 - Puedes añadir el grupo a la página de inicio para acceso rápido:
 - Ve a “Todos los dispositivos” en la pantalla principal,
 - Mantén presionado el grupo,
 - Selecciona “Agregar al inicio”.
-

Otras Funciones:

Puedes crear escenas, cambiar colores, atenuar, conectar con dispositivos inteligentes del hogar, programar horarios, y mucho más.

Solución de Problemas:

Si la primera bombilla no se conecta, asegúrate de estar conectado a una red WiFi de **2.4 GHz**. Con la luminaria conectada al transformador (y el transformador encendido), conecta y desconecta la bombilla **7-8 veces seguidas**. La bombilla debería empezar a parpadear o “respirar”, lo que indica que está en modo de emparejamiento.

Si eso no funciona, deja la bombilla insertada en la luminaria, y **conecta y desconecta el transformador 5 veces seguidas**. Esto reiniciará todo el sistema. Las bombillas deberían comenzar a parpadear o “respirar”.

Let me know if you want a version of this with formatting for a manual or spec sheet.