

**BTX / SKYCO Product Specifications
Roman Shade Systems**

Motorized Roman Shade Systems – BTX / SKYCO DC 28BE Li-Ion RF

1

Part 1 – General

1.01 Summary:

Scope of work is to provide Roman shades that are operated by BTX / SKYCO motorized lift system along with accessories, attachment hardware, and equipment necessary to complete satisfactory installation.

1.02 Turnkey responsibility for motorized Roman shade systems:

- A. To ensure control of responsibility for satisfactory performance and installation of the motorized Roman shade systems, the design, engineering and installation shall be assigned to a single manufacturer and his authorized dealer/installer.
- B. The base building contractor (main contractor) shall provide and coordinate the following items with the window shade contractor/installer for all window shade systems.
 - 1. Shade pockets recessed into ceiling
 - 2. Power wiring
 - 3. Wire conduits as required
 - 4. Duplex outlets and J-boxes

1.03 Submittals

- A. Manufacturing literature to describe assembly, materials, installation instructions, and specific data. Include any pertinent wiring diagrams.
- B. Shop drawings are to include, but are not limited to, all components, fasteners, and installation methods.
- C. Window Systems are custom-built based on measurements taken in the field.

1.04 Warranty

- A. Manufacturer shall provide five (5) year warranty from the date of installation on all shade motors. All operating control and electronic accessory components shall carry a one (1) year limited warranty against defects in materials and workmanship.

1.05 Delivery and storage

- A. Systems shall be delivered to the site in original manufacturer's containers.
- B. Containers shall be uniquely labeled to identify the corresponding window openings and locations.
- C. All materials shall be stored in a dry, secure place protected from weather, water and heat, surface contaminants, construction traffic and all other potential damage.

**BTX / SKYCO Product Specifications
Roman Shade Systems**

Motorized Roman Shade Systems – BTX / SKYCO DC 28BE Li-Ion RF

2

Part 2 – Products

2.01 Manufacturer:

- A. BTX Window Automation
2517 Manana Dr
Dallas, TX 75220 USA
(800) 422-8839
- B. Skyco Shading Systems
3411 W Fordham Ave
Santa Ana, CA 92704
(800) 777-5926

2.02 Components:

- A. BTX / SKYCO AC 28BQE Li-Ion RF tubular motors shall be asynchronous 5V Lithium-Ion rechargeable battery motor rated at 10 watts requiring no electrician or special wiring, and developing 1 NM torque at 25rpm capable of lifting 15 lbs. Motors shall have a fully encapsulated shock resistant motor coil and be moisture resistant and fire resistant. All motors are equipped with a mechanical brake. Motors shall have a thermal protector to prevent overheating. Motor includes internal electronic limit switches. Limit switches shall be easily adjustable in either direction by means of BTX / SKYCO compatible control device.
- B. Tube shall be 38mm extruded aluminum.
- C. Drop-in motor bracket shall be zinc-plated steel and allow both the motor end to drop into the bracket for ease of installation.
- D. Idler insert shall match the tube shape internally and is provided with a round plastic, spring-loaded shaft for mounting in the bracket. Inserts are made from injection molded plastic.
- E. Adaptor Set allows the motor to drive the tube and shall be manufactured from injection molded plastic.

2.03 Controls:

- A. The switching device to activate the system shall be either an RF remote control wall-switch, or via dry contact input. Systems can be controlled individually or as a group. Motors can be integrated into building automation system utilizing BTX / SKYCO wireless RS232 Interface (SmartConnect) or via dry contact input.

**BTX / SKYCO Product Specifications
Roman Shade Systems**

Motorized Roman Shade Systems – BTX / SKYCO DC 28BE Li-Ion RF

3

Part 3 – Execution

3.01 Inspection and Preparation:

- A. Qualified installer shall be responsible for window measurements prior to installation, installation conditions, and preparation of all mounting surfaces.
- B. The charging power supplied shall be 100V-240V to 8.4V 1A AC/DC power transformer. Wiring between primary switch and selected control units shall be in accordance with manufacturer's wiring schematics and specifications. All on site wiring shall be provided by owner.

3.02 Installation:

- A. System installation shall be in accordance with BTX / SKYCO mounting instructions.

3.03 Maintenance:

- A. Lift system components should not require routine maintenance under normal operating conditions.
- B. For fabric care refer to fabric manufacturer's care and use directions.