

Switching processing servers

To switch, go to <https://p.vendista.com/Terminals>

Make sure that the firmware of the terminal is at least 88

Click on the Pencil next to the desired terminal.

Then in the window that opens

1. Change the TID
2. Change the Processing Server
3. Click Send Configuration to Terminal
4. Click save

The screenshot shows a configuration form for a terminal. At the top is a green button labeled "Reboot SIM card". Below it are two dropdown menus: "TID" and "Client", both with a red arrow labeled "1" pointing to them. Below these is a text input field for "ID in the QR system" with the placeholder "Enter QR Code ID". Then is a "Machine model" section with a dropdown menu (red arrow labeled "2" pointing to it) and a green "Select model" button. Below that is a "Processing server:" section with a dropdown menu (red arrow labeled "2" pointing to it) and a green "Send conf. to the terminal" button (red arrow labeled "3" pointing to it). At the bottom is a "Message when issuing code" section.

This screenshot shows the bottom part of the configuration form. It features a large text area for a "Comment" with the text "1234" entered. At the bottom are two buttons: a grey "Cancel" button and a green "Save" button. A red arrow labeled "4" points to the "Save" button.

After that, the terminal will reboot and work with the new processing server.

After switching, make sure to test the payment and check that it was successful and through the required processing.

This can be done via the Transactions report <https://p.vendista.com/Transactions>

Click on the **i** to the right of the test transaction and make sure the Bank and TID are the ones you selected

27		2023-08-23 16:09:09	82440	1	40****8539	1	RRN: 000432989128 ApprovalNumber: 295017 ResponseCode: 0 TID: VP001926 Bank delay: 1 sec Issued goods:
28		2023-08-23 16:08:21	82440	1	40****8539	1	

Test

10093, Armenia, Yerevan, Sayat Nova av., 33/4

25/08/2023 11:23

Purchase

Total1.00 AMD

TerminalVP001924

MerchantVP001924

-A0000006581010

Bank card+8016

CONTACTLESS

Approved

RRN:000434862668

Response code:0

Auth. code445016

It is possible not to select TID for each terminal. The algorithm of TID selection is as follows:
If the terminal has a TID selected, the selected TID is used. If not filled in, any suitable one
belonging to the Reserve Bank is selected. This may be necessary if you have 100 terminals
and 2 TIDs