

Zoom65 comes with the firmware already flashed so you do not need to flash it again.

Needs to import [Json](#) manually to use VIA. If you can't get VIA to recognize the keyboard, you need to flash [firmware](#) on a PC(unable to flash on a Mac), then VIA can be used on Mac as well.

Zoom65 Wireless cannot be flashed via QMK Toolbox or any other method to flash a QMK firmware. You need to use Wuque Studio's own software ([linked below](#)) to flash a new firmware.

Bluetooth/USB wired settings

FN + Space = Wired mode

FN + Z = (long press for 3 seconds) to enter Bluetooth pairing mode. (The caps key flashes green during pairing, and stays on for 3 seconds go off after the pairing is successful)

FN + X = (long press for 3 seconds) to enter Bluetooth pairing mode. (The caps key flashes Blue during pairing, and stays on for 3 seconds go off after the pairing is successful)

Bluetooth Connection method

FN+Z/X (long Press for 3 seconds) to switch to Bluetooth mode. The caps key flashes green during pairing, indicating that it has entered the Bluetooth pairing mode, The computer/mobile phone searches for and connects to the device. After the connection is successful, The caps key stays on for 3 seconds and go off.

If using Bluetooth connection, please switch the keyboard to Bluetooth mode, if using a USB cable connection, please switch the keyboard to USB wired mode. Otherwise, the keyboard cannot be used normally.

FN combinations:

Space+Backspace = Press and plug in the USB to restore factory settings

FN+SHIFT+R = Long press 3S Manually reset the keyboard

Space+N= Turns NKRO On (only in wired mode) must be held before plugging in the keyboard

Fn + Esc = `

Fn + Shift + ESC = ~

Fn + (1 to +) = F1 to F12