SEPAR NET SCRIPT (V. 19-10-2025-2)

- Is this frequency in use? <YOUR CALLSIGN>

1 STATION ID

- Calling the Surrey Emergency Program Amateur Radio Net.
  Calling the Surrey Emergency Program Amateur Radio Net.
- This is <YOUR CALLSIGN—USE PHONETICS>. My name is <YOUR NAME>, and I am located in <YOUR SURREY DISTRICT>. I am assuming the duties of the net control station and for the duration of the net I will use the SEPAR call sign VE7HME.

(FOR WEEKLY NETS ONLY – NET PURPOSE)

- This net meets every Tuesday at 1930 local time on SEPAR channel 1 the VE7RSC North repeater at 147.360 + 600 kHz and a tone of 110.9.
- The purposes of the weekly net are to provide information related to the operation of SEPAR, and to practice effective emergency communication. This is a directed net and all check-ins and traffic are under the direction of the Net Control Station. Please note that general announcements or info related to club events should be saved for the SARC meeting at 2000hrs

(END WEEKLY NET SECTION)

2. NET INSTRUCTIONS

- Are there any stations with emergency or priority traffic? <WAIT FOR TRAFFIC>
- Stations with emergency or priority traffic may break in at any time.
- During an emergency or disaster all SEPAR members are asked to check-in to this repeater - SEPAR Channel 1 - and provide a status report. If this repeater fails to respond, please monitor SEPAR Channel 5 at 146.550 simplex for further instructions.
- After station check-ins, additional instructions may be provided. We request that stations monitor this net and provide updates as they become available. If your availability status changes, please inform net control promptly.

3. STATION CHECKINS AND STATUS REPORTS

- We will now begin taking check-ins. When your district is called, please give your callsign in phonetics and wait to be acknowledged by net control. We encourage stations to use the optional SEPAR Net Protocol to provide their status update as concisely as possible.

- We will take check-ins in the following order:
    - SEPAR Coordinator, or stations on a task
    - Stations with any non-routine traffic
    - City Centre/Whalley,
    - Cloverdale,
    - Fleetwood,
    - Guildford,
    - Newton,
    - South Surrey
    - Echolink.
    - All other Stations
- We now take check-ins from <DISTRICT> <WAIT FOR TRAFFIC>

(repeat until all districts completed)

- Any late or missed check-ins from any area? <WAIT FOR TRAFFIC>

4. Emergency Instructions (FOR EMERGENCIES – SEE NEXT PAGE FOR WEEKLY NET)

- We request that stations monitor this net and provide updates as they become available. If your availability status changes, please inform net control promptly.
- This is VE7HME for the Surrey Emergency Program Amateur Radio program standing by for additional traffic.

(Repeat every 5 minutes until additional instructions are provided, you are relieved, or the net stands down)

4. SIMPLEX CALLS (FOR WEEKLY NET)

- If this were an actual emergency or disaster, additional instructions would be provided at this time.

- We will now proceed with a Roll-call check-in on Simplex.If you wish to participate in the simplex check-in please monitor <SELECTED VHF or UHF FREQUENCY> simplex and respond when called or to relay a response. Net control will call all stations from the repeater check in list in order.
- Stations are asked to respond with a signal report (eg 5/9 or plain language)
- Please do not call in the blind - if you cannot hear net control, wait until sweeps are conducted at the end of the roll. We will resume this repeater net at 1950hrs local.
- This is <YOUR CALLSIGN> as Net control switching now to <SELECTED VHF or UHF FREQUENCY> simplex

MOVE TO SIMPLEX FREQUENCY

- This is VE7HME for the SEPAR weekly net - is this frequency in use? <WAIT FOR TRAFFIC>
- I will now call all stations from the repeater check-in list.

CALL ALL STATIONS FROM THE ROLL

- Are there any unacknowledged stations, or any other stations that wish to check in to the SEPAR net. <WAIT FOR TRAFFIC>

CALL FOR SWEEPS FROM 2 STATIONS IN DIFFERENT AREAS

- We are now returning to SEPAR Channel 1 (VE7RSC N)

SWEEPS TO ALSO ADVISE STATIONS WE ARE RETURNING TO REPEATER.

SWITCH FREQUENCY

5. CLOSING

- This is VE7HME resuming the SEPAR net at 1950local. From a roll-call of <# OF STATIONS ON RPTR CHECKIN) we had (# OF STATIONS ON SIMPLEX) direct and (# RELAYED) relay responses. Thank you to all that were able to participate.
- Do we have any stations with comments or feedback? <WAIT FOR TRAFFIC>
- A reminder that during an emergency or disaster all SEPAR members are asked to check-in to SEPAR Channel 1 - VE7RSC North. If this repeater fails to respond, please monitor SEPAR Channel 5 - 146.550 simplex - for instructions.

- We also encourage stations to check in using our SEPAR Net Protocol available at VE7SAR.net in the SEPAR section
- Thank you all for participating in the SEPAR Net. We thank the Surrey Amateur Radio Club for the useof this repeater. This is <YOUR CALLSIGN> closing the net and returning the frequency to its normal use. 73