

How to Handle Plates with 3RAD v2 Adapter Aliquots

Troy Kieran, Todd Pierson, & Travis C. Glenn

contact: Travis C. Glenn

e-mail: travisg@uga.edu

Originally written: November 2013

Last Update: 28 July, 2015

When you receive the adapters, there is 1.6 nmol of each oligo pair dried in each well, but they are **NOT** annealed. You will need to reconstitute them to the appropriate volume (64 μ L $\rightarrow$ 25 μ M), anneal them, then dilute again (to 2.5 μ M) & aliquot them.

Liquid for reconstitution & annealing (10 mM Tris pH 8, 0.1 mM EDTA, 100 mM NaCl):

For 50 mL of salty TLE, add the following to a 50mL conical:

40 mL dH₂O

500 μ L 1M Tris pH 7.5 to 8

20 μ L 0.5M EDTA pH 8

1 mL of 5 M NaCl (or 5 mL of 1M NaCl)

Fill with distilled water to 50 mL mark.

Protocol:

- 1) Centrifuge the dry plates to get all the primer to the bottom of the wells.
- 2) To limit contamination, peel back the foil cover from the plate one row at a time to reconstitute.
- 3) **Add 64 μ L** of the liquid from above to each well.
 - Use the pipet tip to help scrape the bottom of the well to dislodge any of the adapters that is stuck.
 - Skloosh (pipette up & down) several times to mix.
 - Wait a few minutes.
 - Skloosh several more times to mix.
 - Let the adapters sit in the liquid at room temperature for at least 5 minutes.

The adapters are now at 25 μ M.

- 4) Anneal the adapters together:
 - Use thermalcycler to denature (95°C for 1 min.) & cool slowly (e.g., 0.1°C per sec.).
- 5) Dilute aliquots of the annealed adapters into new labeled strip tubes:
 - **Add 10 μ L of annealed adapters to 90 μ L of salty TLE** (final conc. = 2.5 μ M), for SIX separate strips. [Note: This will leave ~4 μ L behind in the oligo plates (could be worth

getting as much as possible for the Read1 Adapters – they are limiting; but the Read2's are in excess, so leave that behind). Each strip (with 100 µL) can do FOUR full plates.]

- 6) Store the strip tubes of adapters at -20°C.
- 7) Before each use, take adapter aliquots out to thaw and **skloosh well before using!**