

**Step 1.** Preparation before operating GF07 mini GPS tracker

A mini memory card and a SIM card. The SIM card frequency band GSM 850/900/1800/1900MHZ. If you don't know which carrier supports GF07, please check the Country-based mobile phone network frequency coverage.

Note for giffgaf sim (Note - Activate the sim at the giffgaff website before use Top up online using a top up voucher or card, top up £10 or more to activate and receive £5 bonus credit)

**Step 2.** Turn on the GF07 GPS tracker

Open the cap and insert the SIM card in the direction indicated. Insert the mini memory card. The product will automatically turn on the red light for four times and then turn off. After 30 seconds, it will enter the normal standby state.

Note: if it can't read the memory card, please re-insert it.

**Step 3.** GF07 GPS tracker commands and setting**1.** Binding Master Control Number

Editing SMS "000" with mobile phone and sending it to GF07 GPS tracker number, then replying to a short message from mobile phone: [Set: Binding + Master Control Number].

**2.** Separate audio recording

Editing SMS "555" and send to GF07 GPS tracker number, it will reply a text message on mobile phone later: [Snd: recording has begun].

**3.** Sound monitoring

Editing SMS "666" with the mobile phone and send it to GF07 GPS tracker number, and later return a short message: [DT: sound monitoring has been successfully set, and the alarm phone calls back].

When the sound around GF07 GPS tracker is greater than 40dB, GF07 GPS tracker will automatically call the preset mobile phone number.

**4.** GPS track

Using the mobile phone to edit short message "777" and send it to GF07 GPS tracker number. Later, it will reply a Chinese geographical position and Google Map link. When you click this link, the location map and text will appear, which will make the location

**5.** Sound around tracker inquiry

Dialing the number of the card in GF07 GPS tracker directly, and then you can hear the sound around GF07 GPS tracker in a few seconds.

Note: GF07 GPS tracker will not emit any sound and light in the inquiry.

**6.** Positioning trajectory

Using mobile phone to edit SMS "102" and send it to GF07 GPS tracker number. Later, it will reply [account and logs on to the website (It is free), which needs to operate on a computer platform, you can check the real time position.

**7.** Delete memory card content:

Editing SMS "445" with mobile phone and send it to alarm locator number, It will reply a message [ TF, clean up successfully, current capacity ].

8. Check GF07 Mini GPS tracker status:

Edit short message "888" to alarm locator number by mobile phone, and reply to a short message later:  
[All functions of host turn on or off battery capacity binding number, signal strength, boot frequency, GPRS TF card capacity, etc.].

9. Reboot and reset the GF07 Mini GPS tracker

Reboot: Edit the SMS "999" by mobile phone and send it to GF07 GPS tracker number, and wait for 1 minute to recover successfully.

Reset: Edit the short message "444" with the mobile phone and send it to GF07 GPS tracker number, then reply a message later, [Reset: all tasks have been canceled].

Battery level query and indicator

There is battery information in every locate reply message. Turning on the GF07, the indicator light will turn off after 4 times of flash. When the power is low, the indicator will blink fast.

**GF07 Mini GPS tracker Frequently asked questions**

1. Is GF07 GPS tracker SMS global locator waterproof?

It is waterproof design, which makes never worry about rainy and wet day.

2. Why can't send message or make a call to GF07 tracker?

You must insert SIM boot, then it will enable mobile phone signal.

3. Why the memory card can't be read?

Try other memory cards, also you can format the memory card and try it again.

4. How to turn on the GF07 GPS tracker?

If the battery out, it will be turned on automatically when connect power supply.

5. Why GF07 Mini GPS tracker can't be charged?

GF07 Mini GPS tracker should be charged do not take out the SIM card when charging.

6. Whether the platform is free of charge?

GF07 Mini GPS tracker does not require platform fees and is free for life.

7. Can GF07 Mini GPS tracker work in my country?

If your country's carriers the required SIM card frequency band, then it can be worked in your country. If your country support Google map, then the will be better.

**Further from Users:**

1. Bought a SIM with €5 prepaid.
2. Put it in a smartphone to remove the PIN, then put the SIM in the tracker.
3. Charged the tracker.
4. Sent 000 to the phone number of the SIM. Got the correct answer.
5. Sent 777 to the same phone number. Got some Chinese characters plus a link to a map.

6. Clicked on that link and the map showing the location of the tracker.
7. Did not put a memory card and did not try other functions.
8. 777 is all I need.
9. So far, so good. Now let's hope the battery can last at least a week in standby.

**Useful links:**

- <https://youtu.be/woo21Qzns5c>
- <https://youtu.be/CJFpR3erc9o>
- <https://youtu.be/0rwqCXPJpZA>
- <https://youtu.be/ZQTM8nrndAA>
- <https://org-info.mobi/manual/gf-07.htm>

Warning: 1. Must insert SIM card before charging.

Sim card link:

<https://www.ebay.com/itm/122715949254?epid=2164493026&hash=item1c9270c8c6:g:GHYAAOSw4QVZwiS7&amdata=enc%3AAQAHA AAAA4Gd44K0qG5SlyRJusTd7K7%2Fn3eUQIKXQJI3oHlelJgNw%2Fo4bChOb3AYpTkWuEmrlj0pof8wo8E0uJwpTemUjw6HDXcCwLdCiEwpbOG%2Bd3DQtYwkIm5XBqB28Qoimf9eohR46wJwzNhCVxtl13WiVSjK7psM9GUfJDLnqbAp76xwLgd3lEK0bm3b2%2Fc7HBN4xyD6q%2FmwnXi6WR0RVpPV8wxyKI%2BLEwAvCtCIBokbu%2FcCYqAmtkHm1Cp87rYZU7%2FpkGFb61UCzn03GQLJ3pA%2F55%2B6tbmyBVIZ0MuHYloAY1J5n%7Ctkp%3ABk9SR-bgkc hYA>

Notes:

First, please insert the mobile phone card, the TF card does not need to be inserted, after inserting the mobile phone card, see what the indicator light looks like.

If it is long bright, it means that the signal cannot be searched, then please try another mobile phone card. If it is off, it can be used normally. Please see if you can get through the phone and try again.