

Knot Dream'n Operating Check Lists

Opening Up Boat

- I. First On Board
 - a. Turn breaker on Pedestal (dock Shore power)
 - b. House Batteries: Locate and Switch on
 - i. Starboard: under foot of bed, right side
 - ii. Port side: rear closet.
 - c. Water tanks valves: Under cabinet by front door
 - i. Open one of the tank valves
 - d. Control Panel
 - i. Check House battery level. 50% and above
 1. 12 Volt breakers can now be turned on: Turn on Water Pressure breaker for pump
 - ii. Shore 1 breaker on
 - iii. turn transfer breaker on
 - iv. Check voltage levels:
 - v. Needed appliances can now be turned on
 1. Only 15 A can be used at a time or the breaker will trip in the port engine compartment



- II. LPG Operation
 - a. Check LPG tank connections, valves and hose.
 - b. Turn on/open LPG valve at tank
 - c. Turn on LPG Switch on Control Panel
 - d. On top of Stove, Press button and watch for the light to stop blinking.
 - e. When Light is steady, ready to light burners. (Auto Sparks system may need several seconds to bleed air before igniting)
- III. Generator : Turning On (when not on shore power)
 - a. Main Panel by door
 - b. Hold Glow Plug down  for 2-3 Seconds
 - c. While holding Glow plug down, squeeze up on Start Switch, Hold until fully starts
 - d. On Control Panel:
 - i. Turn Generator Breaker on
 - ii. turn transfer breaker on
 - iii. Needed appliances can now be turned on
 - e. Generator off
 - i. hold switch in off position until stops
- IV. Air Conditioners
 - a. If on Shore Power cover Generator
 - b. If running Generator. Cover Shore 1 and Shore2
 - i. Turn on generator 50a Breakers
 - ii. Transfer 32a
 - iii. Turn on AC breakers Port AC and STBD AC.

Closing up boat for more than two days

1. Close window and hatches and lock
2. Leave window in Galley slightly open and both front heads hatch
3. shut off water under counter (by front door)
4. Turn LPG system off (stove, then breaker on panel then valve in aft locker)
5. Turn all breakers off on panel
6. Open fridge
7. take out trash
8. cover microwave
9. turn battery switches off and Davit breaker
10. Lock front door
11. close and lock sliding door
12. turn breaker off at pedestal