

APRS Group Messages

Add a group and name it what you want. Anybody can send to that name all you will get it. Can be helpful to ensure your group gets messages.

FTM400 Radio

Press & hold **DISP SETUP** on right side below power/lock button

Press **APRS**



Go to **Menu 24**



Enter Menu 24 by pushing on the screen or the top dial knob can be pushed in.

Add or edit a group by pushing on the screen or the top dial knob can be pushed in.



Press **enter** once done and it takes you back the Menu 24 screen.

Press **back** 3 times and you should be back on the radio screen.



Now to test if it works. Send a message to HAMHI on APRS.



Enter HAMHI in to: field or callsign, put something in the text field, I put test. Then press MSG/TX to send.

The photo below is the end result back to my radio. Since I have HAMHI in my Message Group I got the message and it shows it that everyone that has HAMHI would have got it. This depends on their radio being on, the Group is set up and within range of the sender or a relay station / igate.

